

# Lab Exercise

## Test Case Editor



1. Find the **Step Properties** menu for a step
2. Find the procedure properties menu for the **main** procedure
3. Find the general page and add your name to the owner field
4. Navigate back to the steps tab, and change the **show interfaces brief** step to check **ge-0/0/1** instead of **ge-0/0/0**

# Lab Exercise

## Analysis Rules

1. Add an analysis rule to check the switch's current firmware
  1. Select the step containing the command **show chassis firmware**
  2. In the response tab, click the **Add Analysis Rule** button
  3. Select **Validate something in the response**
  4. Select **The response contains a specified string**
  5. Highlight the firmware version number and click **Next**
  6. Uncheck **Use auto-generated message** for both cases
  7. Replace the default messages with descriptive, user-friendly messages
  8. Complete the wizard

# Lab Exercise

## Analysis Rules

2. Add an analysis rule to pass the test if our primary interface is up
  1. Select the step containing the command **show interfaces ge-0/0/0 brief**
  2. In the response tab, click the **Add Analysis Rule** button
  3. Select **Validate something in the response**
  4. Select **The response contains a specified string**
  5. Highlight text that shows the primary interface is up and click **Next**
  6. Uncheck **Use auto-generated message** for both cases
  7. Replace the default messages with descriptive, user-friendly messages
  8. Complete the wizard
  
3. Execute the test